



## Specification

|              |                                   |         |
|--------------|-----------------------------------|---------|
| Voltage      | 20 - 28Vdc                        |         |
| Current      | 112mm (4")                        | 18mA    |
|              | 152mm (6")                        | 25mA    |
|              | 203mm (8")                        | 28mA    |
| Sound Output | 112mm (4")                        | 84dB(A) |
|              | 152mm (6")                        | 95dB(A) |
|              | 203mm (8")                        | 97dB(A) |
| Monitoring   | Reverse polarity                  |         |
| Temperature  | - 10°C to + 55°C                  |         |
| Protection   | IP21C                             |         |
| Construction | Gong -Steel, Base - Polycarbonate |         |
| Weight       | 0.45Kg                            |         |
| Colours      | Gong - Red, grey or black         |         |
|              | Base - Black                      |         |

## CF Bell 24 Volt

### MOTORISED

Bells still remain a popular choice for many applications such as schools where they can sometimes be used as a signal for non fire purposes such as class change. All CF bells incorporate highly efficient rotary centrifugal movements combining high sound output with low current consumption.

- 3 GONG SIZES
- HIGH SOUND OUTPUT
- LOW CURRENT CONSUMPTION
- SIMPLE INSTALLATION
- MULTIFIXING BASEPLATE